



SH POWER



SH SERVICE
Your Reliable Source of Power

Brand: SH POWER | Model: SH8500ES-DF

SPECIFICATION

Generator

| | |
|---------------------|-------------|
| COUNTRY OF ORIGIN | China |
| COUNTRY OF ASSEMBLY | China |
| BRAND | SH POWER |
| MODEL | SH8500ES-DF |
| RATED OUTPUT | 7.0kW |
| MAXIMUM OUTPUT | 7.5kW |
| RATED AMPERE | 32A |
| DC OUTPUT | 12V / 18A |

Engine

| | |
|------------------------------|------------------------|
| MODEL | 192FD |
| TYPE | 4-Stroke OHV |
| DISPLACEMENT | 460 cc |
| SPEED | 3000 rpm |
| MAXIMUM ENGINE POWER | 12kw/16hp |
| FUEL | Duel Fuel (Petrol/LPG) |
| FUEL TANK CAPACITY | 25 Ltr |
| FUEL CONSUMPTION (100% Load) | 3 Ltr/Hr |
| CONTINUOUS OPERATION HOUR | 8.3 Hr |
| ENGINE OIL CAPACITY | 1.2 Ltr |
| OIL ALERT SYSTEM | Standard |
| STARTING SYSTEM | Recoil & Electric |
| NOSIE LEVEL @7M | 74dBA |

Dimension & Weight

| | |
|-----------------------|-------------|
| DIMENSIONS LXWXH (MM) | 695x525x580 |
| NET WEIGHT | 79 kg |

CORPORATE OFFICE

Paramount Concord (1st Floor), 9/1-2,
Hatkhola Road, Tikatuli, Dhaka-1203
Mobile: 01740088182, 01733664414

NAWABPUR BRANCH

Kashem Plaza, 111/112, Madan Pal
Lane, Nawabpur, Dhaka-1100.
Mobile: 01712015344, 01979155390

REGISTERED ADDRESS

116/3/4, Nawabpur Road,
Dhaka-1100.



ALTERNATOR

| | |
|------------------|--------------|
| BRAND | SENCI |
| MODEL | YIHUΦ190*165 |
| CARBON TYPE | TFD |
| POWER FACTOR | 1 Cos |
| NO. OF PHASE | Single Phase |
| AC VOLTAGE | 220V |
| VOLTAGE SYSTEM | AVR |
| FREQUENCY | 50 Hz |
| INSULATION CLASS | F |

100% Full Copper