

Brand: SONALI | Model: HG13000CXA

SPECIFICATION

Generator

COUNTRY OF ORIGIN	China
COUNTRY OF ASSEMBLY	China
BRAND	Sonali
MODEL	HG13000CXA
RATED OUTPUT	10.0KW
MAXIMUM OUTPUT	11.0KW
RATED AMPERE	45A
DC OUTPUT	12V / 36A
RECEPTACLE	EU Socket 50A

Engine

MODEL	HONDA GX690 (Japan)
TYPE	4-Stroke OHV
DISPLACEMENT CC/HP	688cc (22.1hp)
SPEED	3000 RPM
MAXIMUM ENGINE POWER	16.5kw/22.1hp
FUEL TANK CAPACITY	40Ltr
FUEL CONSUMPTION (100% Load)	5Ltr/Hr
CONTINUOUS OPERATION HOUR	8Hr
ENGINE OIL CAPACITY	2Ltr
OIL ALERT SYSTEM	Standard
STARTING SYSTEM	Electric
NOISE LEVEL @7M	80dBA

Dimension & Weight

DIMENSIONS LXWXH (MM)	1115X700X1075
NET WEIGHT	185kg



ALTERNATOR

BRAND	SENCI
MODEL	SCB230-10.0
CARBON TYPE	TFD
POWER FACTOR	1 Cos
NO. OF PHASE	Single Phase
AC VOLTAGE	220V
VOLTAGE SYSTEM	AVR
FREQUENCY	50 Hz
INSULATION CLASS	F

100% Full Copper

CORPORATE OFFICE

Paramount Concord (1st Floor), 9/1-2,
Hatkhola Road, Tikatuli, Dhaka-1203
Mobile: 01740088182, 01733664414

NAWABPUR BRANCH

Kashem Plaza, 111/112, Madan Pal
Lane, Nawabpur, Dhaka-1100.
Mobile: 01712015344, 01979155390

REGISTERED ADDRESS

116/3/4, Nawabpur Road,
Dhaka-1100.